



kramer

VGAA-OUT2-F16/F34

2-Channel VGA with Analog Audio Output
Card

| Kramer Core



VGAA-OUT2-F16/F34 is a two-channel VGA with analog audio output card for the VS-1616 or VS-34FD Series Modular Multi-Format Digital Matrix Switchers. The VGAA-OUT2-F16/F34 outputs two VGA with analog audio signals from the chassis. Audio output is accessed by connecting the supplied Kramer VGA with audio cables to each VGA port

FEATURES

- Max. Bandwidth - 450MHz
- HDTV Compatible
- Analog Audio Over Breakaway Connector



kramer

TECHNICAL SPECIFICATIONS

PORTS:	2 VGA on 15-pin HD connectors, 2 unbalanced analog audio on 3.5mm mini jack connectors (accessible via C GF/GMAF-30 cables)
BANDWIDTH:	450MHz
MAXIMUM RANGE:	10m (32ft)
POWER CONSUMPTION:	5.5W
OPERATING TEMPERATURE:	0° to +40°C (32° to 104°F)
STORAGE TEMPERATURE:	-40° to +70°C (-40° to 158°F)
HUMIDITY:	10% to 90%, RHL non-condensing
SAFETY REGULATORY COMPLIANCE:	CE
ENVIRONMENTAL REGULATORY COMPLIANCE:	Complies with appropriate requirements of RoHs and WEEE
INCLUDED ACCESSORIES:	2 C-GF/GMAF-30 cables
Product Dimensions	25.20cm x 13.00cm x 2.00cm (9.92" x 5.12" x 0.79") W, D, H
Product Weight	0.3kg (0.7lbs) approx
Shipping Dimensions	16.50cm x 30.00cm x 6.00cm (6.50" x 11.81" x 2.36") W, D, H
Shipping Weight	0.5kg (1.0lbs) approx



kramer

CONFIGURATIONS

VGAA-OUT2-F16/STANDALONE	2-Channel VGA with Analog Audio Output Card for VS-1616D and VS-1616DN-EM Modular Matrixes
--------------------------	--

VGAA-OUT2-F34(ADP+F16)/STANDALONE	2-Channel VGA with Analog Audio Output Card for VS-34FD Modular Matrix
-----------------------------------	--
